

ET-CNT6P3 (P-ET-A-00097)

UNIVERSAL TARGET DISPLAY BOARD

ET-CNT6P3 is a large board suitable for large factory because it's visible for 50m. It uses in Manufacture Target Counter, Timetable Counter and etc with a large 6 Digit to display. There's accessories for support such as 16-CH. Counter (ET-MC16) users can expand their target of board in the future and it's cheaper than other products.



Specification ET - CNT6P3

Operating Voltage Supply:	220VAC/50Hz
No of Digit Display:	6 Digit of 7 - Segment X 3
Display Type:	LED 7 - Segment (Dot LED 5mm. Super Bright)
No of Input Signal:	2 Input (1 Signal Counter & 1 Reset Counter) Optoisolation
Input Signal Counter Type:	Contact Switch or +12V Pulse Signal
Input Reset Counter Type:	Contact Switch or +12V Pulse Signal
Counter Speed:	10 - CPS (10Hz)
No of Output Signal:	2 Output (1 Counter Output & 1 Alarm Output)
Output Counter Type:	Open Collector (MAXIMUM VOLT AGE+24V)
Output Alarm Type:	Relay Contact 2A/250VAC (NO-COMMON-NC)
Battery Backup Time:	2 Year Data Backup
Operation Mode:	4 Mode Programmable Operation :Counter Mode :Terminal Display Mode (RS485) :Serial Display Mode (RS232):Display Self-Test Mode
Programmable Mode Device:	RS232 Keyboard Switch BOX , Computer PC With RS232 + SOFTWARE PROGRAM
Display Dimension (W x L):	11.5 x 52.5 cm (4.5 x 20.6 Inch)
BOX Dimension (W x L x D):	50.5 x 76 x 7cm (20 x 30.3 x 2.7 Inch)

- COUNT-UP PROGRAM (000000-999999)
- COUNT-DOWN PROGRAM (999999-000000)
- DIVIDE COUNTER PROGRAM
- PRESET COUNTER PROGRAM
- TARGET COUNTER PROGRAM
- INPUT COUNTER PROGRAM AS +12 V SIGNAL PULSE OR CONTACT SWITCH INPUT OR OPEN COLLECTOR RELAY AND BE ABLE TO SET DEBOUNCE PROGRAM
- SET PROGRAM WITH ALARM AND RELATE WITH TARGET COUNTER, 1-CH. RELAY OUTPUT OF ALARM AS NO, NC, AND COMMON
- BATTERY BACK UP
- ET-CNT6P3 INCLUDES;

1. Board with Metal Box
2. Key Board with Program (ET-KEY 232)and 3m. KEY Cable
3. DB 25 PIN Male Port with Cover
4. User Manual, CD-ROM



ET-CNT6P3 PLUS

Specifications of ET-CNT6P3 PLUS is as same as ET-CNT6P3, but it is different in shape and small size

- 1.DISPLAY 4 DIGIT 3 LINES 7-SEGMENT 2.3 INCH RED LED
- 2.BOX DIMENSION (W x L x D) 36 x 40 x 10 CM.

(P-ET-A-00188)



ET-CNT6P3 PLUS INCLUDES;

1. BOARD WITH PLASTIC BOX
2. KEY BOARD USING WITH ET-KEY232 AND 3M KEY CABLE
3. DB 25 PIN PORT WITH COVER
4. USER AMNUAL
5. CD-ROM
6. RS232 DB 9 PIN HEADER CNT-6



- Adaptation • Be able to expand Display more than 1 point by using with ET-CNT6P 6 Digit 1 line Display for 1.2 KM. further
- Accessories • 16-CH.ET-MC16 MULTI COUNTER (OPTION) connecting with ET-CNT6P to expand channel Price

ET-CNT4 P2 TARGET TIME

It's a Counter that has 4 digits with 2 rows.

Number is 2.3 inch red LED 7-Segment.

Green and Red LED display state operation.

(P-ET-A-00318)



- TARGET can be set to count up one by one automatically from 1 to 999 seconds
- ACTUAL displays result from counting up of incoming INPUT
- GREEN LED will be ON if ACTUAL is greater or equal to TARGET; RED LED will be ON if ACTUAL is lesser than TARGET
- BOX DEMENSION (W x L x D): 45 x 25 x 10 cm.

ET-CNT4 P2 TARGET TIME consists:

1. Board with plastic box
2. KEY BOARD (ET-KEY232) and cable
3. Connector Male DB 25PIN with COVER
4. User's Manual

